

# Helpman ZLE 424-8-K-ZQ

## Specifications

|                        |                              |
|------------------------|------------------------------|
| La marque              | Helpman                      |
| Type                   | ZLE 424-8-K-ZQ               |
| Capacité kW            | 28,7                         |
| Réfrigérant            | NH 3 (ammonia)               |
| Nombre de ventilateurs | 2                            |
| Espace Fan in mm       | 8                            |
| Dégivrage              | None                         |
| m <sup>3</sup> /h      | 20.900                       |
| Tailles                | 2900x1050x1080 mm<br>(LxWxH) |
| Volume                 | 50,8 dm <sup>3</sup>         |
| Poids                  | 560 kg                       |
| Stock                  | 3                            |



## Description

### Used Helpman ZLE 424-8-K-ZQ

Used Helpman ZLE 424-8-K-ZQ/-I-Z evaporator on NH3. Complete with 2 ABB MXMA 080B fans - 50 Hz - 0,75 kW - 900 RPM and an airflow of 20.900 m<sup>3</sup>/h.

\*All components of this used evaporator will be tested on good working, leak free condition (electro engines), coils, bearings) Choosing HOSBV means buying with warranty. We perform a industrial cleaning. Also, we can arrange your shipment.



| HELPMAN                    |                             | Apparatenfabriek Helpman BV<br>Peizerweg 97<br>NL - 9727 AJ, Groningen |  |
|----------------------------|-----------------------------|--|--|
| Type                       | ZLE 424-8-K-ZQ/-I-Z- (SOCK) |  |  |
| Serial nr.                 | 930159                      |  |  |
| Medium                     | NH3                         |  |  |
| Min/max workingtemperature | -40/55                      | °C   |  |
| Design/testpressure        | 20/25                       | bar  |  |
| Volume                     | 50.8                        | dm <sup>3</sup>  |  |
| Weight: (empty)            | 560                         | kg   |  |
| Isolatie met Armaflex 1/2" | 99                          |  |  |



